

**CEN**

**CWA 16374-8**

**WORKSHOP**

December 2011

**AGREEMENT**

---

ICS 35.240.40

English version

**Extensions for Financial Services (XFS) interface specification  
Release 3.20 - Part 8: Depository Device Class Interface  
Programmer's Reference**

This CEN Workshop Agreement has been drafted and approved by a Workshop of representatives of interested parties, the constitution of which is indicated in the foreword of this Workshop Agreement.

The formal process followed by the Workshop in the development of this Workshop Agreement has been endorsed by the National Members of CEN but neither the National Members of CEN nor the CEN-CENELEC Management Centre can be held accountable for the technical content of this CEN Workshop Agreement or possible conflicts with standards or legislation.

This CEN Workshop Agreement can in no way be held as being an official standard developed by CEN and its Members.

This CEN Workshop Agreement is publicly available as a reference document from the CEN Members National Standard Bodies.

CEN members are the national standards bodies of Austria, Belgium, Bulgaria, Croatia, Cyprus, Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Switzerland and United Kingdom.



EUROPEAN COMMITTEE FOR STANDARDIZATION  
COMITÉ EUROPÉEN DE NORMALISATION  
EUROPÄISCHES KOMITEE FÜR NORMUNG

**Management Centre: Avenue Marnix 17, B-1000 Brussels**

---

© 2011 CEN All rights of exploitation in any form and by any means reserved worldwide for CEN national Members.

Ref. No.:CWA 16374-8:2011 E

## Table of Contents

---

Foreword .....	3
<b>1. Introduction.....</b>	<b>6</b>
1.1 Background to Release 3.20 .....	6
1.2 XFS Service-Specific Programming.....	6
<b>2. Depository Unit.....</b>	<b>7</b>
<b>3. References .....</b>	<b>8</b>
<b>4. Info Commands .....</b>	<b>9</b>
4.1 WFS_INF_DEP_STATUS .....	9
4.2 WFS_INF_DEP_CAPABILITIES.....	14
<b>5. Execute Commands .....</b>	<b>17</b>
5.1 WFS_CMD_DEP_ENTRY .....	17
5.2 WFS_CMD_DEP_DISPENSE .....	19
5.3 WFS_CMD_DEP_RETRACT .....	20
5.4 WFS_CMD_DEP_RESET_COUNT.....	22
5.5 WFS_CMD_DEP_RESET .....	23
5.6 WFS_CMD_DEP_SET_GUIDANCE_LIGHT .....	24
5.7 WFS_CMD_DEP_SUPPLY_REPLENISH .....	26
5.8 WFS_CMD_DEP_POWER_SAVE_CONTROL .....	27
<b>6. Events.....</b>	<b>28</b>
6.1 WFS_SRVE_DEP_ENVTAKEN.....	28
6.2 WFS_EXEE_DEP_ENVDEPOSITED.....	29
6.3 WFS_EXEE_DEP_DEPOSITERROR .....	30
6.4 WFS_USRE_DEP_DEPTHRESHOLD.....	31
6.5 WFS_USRE_DEP_TONERTHRESHOLD .....	32
6.6 WFS_USRE_DEP_ENVTHRESHOLD.....	33
6.7 WFS_SRVE_DEP_CONTINSERTED .....	34
6.8 WFS_SRVE_DEP_CONTREMOVED .....	35
6.9 WFS_SRVE_DEP_ENVINSERTED .....	36
6.10 WFS_SRVE_DEP_MEDIADETECTED.....	37
6.11 WFS_EXEE_DEP_INSERTDEPOSIT .....	38
6.12 WFS_SRVE_DEP_DEVICEPOSITION .....	39
6.13 WFS_SRVE_DEP_POWER_SAVE_CHANGE.....	40
<b>7. C - Header file .....</b>	<b>41</b>

## Foreword

---

This CWA is revision 3.20 of the XFS interface specification.

This CEN Workshop Agreement has been drafted and approved by a Workshop of representatives of interested parties on 2011-06-29, the constitution of which was supported by CEN following the public call for participation made on 1998-06-24. The specification is continuously reviewed and commented in the CEN/ISSS Workshop on XFS. It is therefore expected that an update of the specification will be published in due time as a CWA, superseding this revision 3.20.

A list of the individuals and organizations which supported the technical consensus represented by the CEN Workshop Agreement is available to purchasers from the CEN-CENELEC Management Centre. These organizations were drawn from the banking sector. The CEN/ISSS XFS Workshop gathered suppliers as well as banks and other financial service companies.

The CWA is published as a multi-part document, consisting of:

Part 1: Application Programming Interface (API) - Service Provider Interface (SPI) - Programmer's Reference

Part 2: Service Classes Definition - Programmer's Reference

Part 3: Printer and Scanning Device Class Interface Programmer's Reference

Part 4: Identification Card Device Class Interface - Programmer's Reference

Part 5: Cash Dispenser Device Class Interface - Programmer's Reference

Part 6: PIN Keypad Device Class Interface - Programmer's Reference

Part 7: Check Reader/Scanner Device Class Interface - Programmer's Reference

Part 8: Depository Device Class Interface - Programmer's Reference

Part 9: Text Terminal Unit Device Class Interface - Programmer's Reference

Part 10: Sensors and Indicators Unit Device Class Interface - Programmer's Reference

Part 11: Vendor Dependent Mode Device Class Interface - Programmer's Reference

Part 12: Camera Device Class Interface - Programmer's Reference

Part 13: Alarm Device Class Interface - Programmer's Reference

Part 14: Card Embossing Unit Class Interface - Programmer's Reference

Part 15: Cash-In Module Device Class Interface - Programmer's Reference

Part 16: Card Dispenser Device Class Interface - Programmer's Reference

Part 17: Barcode Reader Device Class Interface - Programmer's Reference

Part 18: Item Processing Module Device Class Interface- Programmer's Reference

Parts 19 - 28: Reserved for future use.

Parts 29 through 47 constitute an optional addendum to this CWA. They define the integration between the SNMP standard and the set of status and statistical information exported by the Service Providers.

Part 29: XFS MIB Architecture and SNMP Extensions

Part 30: XFS MIB Device Specific Definitions - Printer Device Class

Part 31: XFS MIB Device Specific Definitions - Identification Card Device Class

Part 32: XFS MIB Device Specific Definitions - Cash Dispenser Device Class

Part 33: XFS MIB Device Specific Definitions - PIN Keypad Device Class

Part 34: XFS MIB Device Specific Definitions - Check Reader/Scanner Device Class

Part 35: XFS MIB Device Specific Definitions - Depository Device Class

Part 36: XFS MIB Device Specific Definitions - Text Terminal Unit Device Class

Part 37: XFS MIB Device Specific Definitions - Sensors and Indicators Unit Device Class

Part 38: XFS MIB Device Specific Definitions - Camera Device Class

## **CWA 16374-8:2011 (E)**

Part 39: XFS MIB Device Specific Definitions - Alarm Device Class

Part 40: XFS MIB Device Specific Definitions - Card Embossing Unit Device Class

Part 41: XFS MIB Device Specific Definitions - Cash-In Module Device Class

Part 42: Reserved for future use.

Part 43: XFS MIB Device Specific Definitions - Vendor Dependent Mode Class

Part 44: XFS MIB Application Management

Part 45: XFS MIB Device Specific Definitions - Card Dispenser Device Class

Part 46: XFS MIB Device Specific Definitions - Barcode Reader Device Class

Part 47: XFS MIB Device Specific Definitions - Item Processing Module Device Class

Parts 48 - 60 are reserved for future use.

Part 61: Application Programming Interface (API) - Service Provider Interface (SPI) - Migration from Version 3.10 (see CWA 15748) to Version 3.20 (this CWA) - Programmer's Reference

Part 62: Printer and Scanning Device Class Interface - Migration from Version 3.10 (CWA 15748) to Version 3.20 (this CWA) - Programmer's Reference

Part 63: Identification Card Device Class Interface - Migration from Version 3.10 (see CWA 15748) to Version 3.20 (this CWA) - Programmer's Reference

Part 64: Cash Dispenser Device Class Interface - Migration from Version 3.10 (see CWA 15748) to Version 3.20 (this CWA) - Programmer's Reference

Part 65: PIN Keypad Device Class Interface - Migration from Version 3.10 (see CWA 15748) to Version 3.20 (this CWA) - Programmer's Reference

Part 66: Check Reader/Scanner Device Class Interface - Migration from Version 3.10 (see CWA 15748) to Version 3.20 (this CWA) - Programmer's Reference

Part 67: Depository Device Class Interface - Migration from Version 3.10 (see CWA 15748) to Version 3.20 (this CWA) - Programmer's Reference

Part 68: Text Terminal Unit Device Class Interface - Migration from Version 3.10 (see CWA 15748) to Version 3.20 (this CWA) - Programmer's Reference

Part 69: Sensors and Indicators Unit Device Class Interface - Migration from Version 3.10 (see CWA 15748) to Version 3.20 (this CWA) - Programmer's Reference

Part 70: Vendor Dependent Mode Device Class Interface - Migration from Version 3.10 (see CWA 15748) to Version 3.20 (this CWA) - Programmer's Reference

Part 71: Camera Device Class Interface - Migration from Version 3.10 (see CWA 15748) to Version 3.20 (this CWA) - Programmer's Reference

Part 72: Alarm Device Class Interface - Migration from Version 3.10 (see CWA 15748) to Version 3.20 (this CWA) - Programmer's Reference

Part 73: Card Embossing Unit Device Class Interface - Migration from Version 3.10 (CWA 15748) to Version 3.20 (this CWA) - Programmer's Reference

Part 74: Cash-In Module Device Class Interface - Migration from Version 3.10 (see CWA 15748) to Version 3.20 (this CWA) - Programmer's Reference

Part 75: Card Dispenser Device Class Interface - Migration from Version 3.10 (see CWA 15748) to Version 3.20 (this CWA) - Programmer's Reference

Part 76: Barcode Reader Device Class Interface - Migration from Version 3.10 (see CWA 15748) to Version 3.20 (this CWA) - Programmer's Reference

Part 77: Item Processing Module Device Class Interface - Migration from Version 3.10 (see CWA 15748) to Version 3.20 (this CWA) - Programmer's Reference

In addition to these Programmer's Reference specifications, the reader of this CWA is also referred to a complementary document, called Release Notes. The Release Notes contain clarifications and explanations on the CWA specifications, which are not requiring functional changes. The current version of the Release Notes is available online from <http://www.cen.eu/cen/pages/default.aspx>.

The information in this document represents the Workshop's current views on the issues discussed as of the date of publication. It is furnished for informational purposes only and is subject to change without notice. CEN/ISSS makes no warranty, express or implied, with respect to this document.

The formal process followed by the Workshop in the development of the CEN Workshop Agreement has been endorsed by the National Members of CEN but neither the National Members of CEN nor the CEN-CENELEC Management Centre can be held accountable for the technical content of the CEN Workshop Agreement or possible conflict with standards or legislation. This CEN Workshop Agreement can in no way be held as being an official standard developed by CEN and its members.

The final review/endorsement round for this CWA was started on 2011-06-23 and was successfully closed on 2011-07-23. The final text of this CWA was submitted to CEN for publication on 2011-08-26.

This CEN Workshop Agreement is publicly available as a reference document from the National Members of CEN: Austria, Belgium, Bulgaria, Croatia, Cyprus, Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Switzerland and the United Kingdom.

Comments or suggestions from the users of the CEN Workshop Agreement are welcome and should be addressed to the CEN-CENELEC Management Centre.

#### Revision History:

3.00	October 18, 2000	Initial release.
3.10	November 29, 2007	For a description of changes from version 3.00 to version 3.10 see the DEP 3.10 Migration document.
3.20	March 2nd, 2011	For a description of changes from version 3.10 to version 3.20 see the DEP 3.20 Migration document.

## 1. Introduction

---

### 1.1 Background to Release 3.20

---

The CEN/ISSS XFS Workshop aims to promote a clear and unambiguous specification defining a multi-vendor software interface to financial peripheral devices. The XFS (eXtensions for Financial Services) specifications are developed within the CEN/ISSS (European Committee for Standardization/Information Society Standardization System) Workshop environment. CEN/ISSS Workshops aim to arrive at a European consensus on an issue that can be published as a CEN Workshop Agreement (CWA).

The CEN/ISSS XFS Workshop encourages the participation of both banks and vendors in the deliberations required to create an industry standard. The CEN/ISSS XFS Workshop achieves its goals by focused sub-groups working electronically and meeting quarterly.

Release 3.20 of the XFS specification is based on a C API and is delivered with the continued promise for the protection of technical investment for existing applications. This release of the specification extends the functionality and capabilities of the existing devices covered by the specification, but does not include any new device classes. Notable major enhancements include Mixed Media processing to allow mixed cash and check accepting, as well as the addition of new commands to the CIM, PTR and IDC to allow better support of the Japanese marketplace.

### 1.2 XFS Service-Specific Programming

---

The service classes are defined by their service-specific commands and the associated data structures, error codes, messages, etc. These commands are used to request functions that are specific to one or more classes of Service Providers, but not all of them, and therefore are not included in the common API for basic or administration functions.

When a service-specific command is common among two or more classes of Service Providers, the syntax of the command is as similar as possible across all services, since a major objective of XFS is to standardize function codes and structures for the broadest variety of services. For example, using the **WFSExecute** function, the commands to read data from various services are as similar as possible to each other in their syntax and data structures.

In general, the specific command set for a service class is defined as a superset of the specific capabilities likely to be provided by the developers of the services of that class; thus any particular device will normally support only a subset of the defined command set.

There are three cases in which a Service Provider may receive a service-specific command that it does not support:

The requested capability is defined for the class of Service Providers by the XFS specification, the particular vendor implementation of that service does not support it, and the unsupported capability is *not* considered to be fundamental to the service. In this case, the Service Provider returns a successful completion, but does no operation. An example would be a request from an application to turn on a control indicator on a passbook printer; the Service Provider recognizes the command, but since the passbook printer it is managing does not include that indicator, the Service Provider does no operation and returns a successful completion to the application.

The requested capability is defined for the class of Service Providers by the XFS specification, the particular vendor implementation of that service does not support it, and the unsupported capability *is* considered to be fundamental to the service. In this case, a `WFS_ERR_UNSUPP_COMMAND` error is returned to the calling application. An example would be a request from an application to a cash dispenser to dispense coins; the Service Provider recognizes the command but, since the cash dispenser it is managing dispenses only notes, returns this error.

The requested capability is *not* defined for the class of Service Providers by the XFS specification. In this case, a `WFS_ERR_INVALID_COMMAND` error is returned to the calling application.

This design allows implementation of applications that can be used with a range of services that provide differing subsets of the functionalities that are defined for their service class. Applications may use the **WFSGetInfo** and **WFSAsyncGetInfo** commands to inquire about the capabilities of the service they are about to use, and modify their behavior accordingly, or they may use functions and then deal with `WFS_ERR_UNSUPP_COMMAND` error returns to make decisions as to how to use the service.

## 2. Depository Unit

---

This specification describes the functionality of the services provided by the Depository (DEP) services under XFS, by defining the service-specific commands that can be issued, using the **WFSGetInfo**, **WFSAsyncGetInfo**, **WFSExecute** and **WFSAsyncExecute** functions.

A Depository is used for the acceptance and deposit of media into the device or terminal. There are two main types of depository: an envelope depository for the deposit of media in envelopes and a night safe depository for the deposit of bags containing bulk media.

An envelope depository accepts media, prints on the media and deposits the media into a holding container or bin. Some envelope depositories offer the capability to dispense an envelope to the customer at the start of a transaction. The customer takes this envelope, fills in the deposit media, possibly inscribes it and puts it into the deposit slot. The envelope is then accepted, printed and transported into a deposit container.

The envelope dispense mechanism may be part of the envelope depository device mechanism with the same entry/exit slot or it may be a separate mechanism with separate entry/exit slot.

Envelopes dispensed and not taken by the customer can be retracted back into the device. When the dispenser is a separate mechanism the envelope is retracted back into the dispenser container. When the dispenser is a common mechanism the envelope is retracted into the depository container.

A night safe depository normally only logs the deposit of a bag and does not print on the media.

### 3. References

---

---

1. XFS Application Programming Interface (API)/Service Provider Interface (SPI), Programmer's Reference Revision 3.20
--

## 4. Info Commands

---

### 4.1 WFS\_INF\_DEP\_STATUS

---

**Description** This command reports the full range of information available, including the information that is provided by the Service Provider.

**Input Param** None.

**Output Param** LPWFSDEPSTATUS lpStatus;

```
typedef struct _wfs_dep_status
{
    WORD                fwDevice;
    WORD                fwDepContainer;
    WORD                fwDepTransport;
    WORD                fwEnvSupply;
    WORD                fwEnvDispenser;
    WORD                fwPrinter;
    WORD                fwToner;
    WORD                fwShutter;
    WORD                wNumOfDeposits;
    LPSTR               lpSzExtra;
    DWORD               dwGuidLights[WFS_DEP_GUIDLIGHTS_SIZE];
    WORD                fwDepositLocation;
    WORD                wDevicePosition;
    USHORT              usPowerSaveRecoveryTime;
    WORD                wAntiFraudModule;
} WFSDEPSTATUS, *LPWFSDEPSTATUS;
```

*fwDevice*

Specifies the state of the Depository device as one of the following flags:

Value	Meaning
WFS_DEP_DEVONLINE	The device is online (i.e. powered on and operable).
WFS_DEP_DEVOFFLINE	The device is off-line (e.g. the operator has taken the device offline by turning a switch or pulling out the device).
WFS_DEP_DEVPOWEROFF	The device is powered off or physically not connected.
WFS_DEP_DEVNODEVICE	There is no device intended to be there; e.g. this type of self service machine does not contain such a device or it is internally not configured.
WFS_DEP_DEVHWERROR	The device is inoperable due to a hardware error. The device is present but a hardware fault prevents it from being used.
WFS_DEP_DEVUSERERROR	The device is present but a person is preventing proper operation. The application should suspend the device operation or remove the device from service until the Service Provider generates a device state change event indicating the condition of the device has changed, i.e. the error is removed or a permanent error condition has occurred.
WFS_DEP_DEVBUSY	The device is busy and not able to process an Execute command at this time.
WFS_DEP_DEVFRAUDATTEMPT	The device is present but is inoperable because it has detected a fraud attempt.
WFS_DEP_DEVPOTENTIALFRAUD	The device has detected a potential fraud attempt and is capable of remaining in service. In this case the application should make the decision as to whether to take the device offline.

*fwDepContainer*

Specifies the state of the deposit container that contains the deposited envelopes or bags as one of the following flags:

Value	Meaning
WFS_DEP_DEPOK	The deposit container is in a good state.
WFS_DEP_DEPHIGH	The deposit container is almost full (threshold).
WFS_DEP_DEPFULL	The deposit container is full.
WFS_DEP_DEPINOP	The deposit container is inoperable.
WFS_DEP_DEPMISSING	The deposit container is missing.
WFS_DEP_DEPUNKNOWN	Due to a hardware error or other condition, the state of the deposit container cannot be determined.
WFS_DEP_DEPNOTSUPP	The physical device is not able to determine the status of the deposit container.

*fwDepTransport*

Specifies the state of the deposit transport mechanism that transports the envelope into the deposit container. Specified as one of the following flags:

Value	Meaning
WFS_DEP_DEPOK	The deposit transport is in a good state.
WFS_DEP_DEPINOP	The deposit transport is inoperative due to a hardware failure or media jam.
WFS_DEP_DEPUNKNOWN	Due to a hardware error or other condition, the state of the deposit transport cannot be determined.
WFS_DEP_DEPNOTSUPP	The physical device has no deposit transport.

*fwEnvSupply*

Specifies the state of the envelope supply unit as one of the following flags:

Value	Meaning
WFS_DEP_ENVOK	The envelope supply unit is in a good state (and locked).
WFS_DEP_ENVLOW	The envelope supply unit is present but low.
WFS_DEP_ENVEMPTY	The envelope supply unit is present but empty. No envelopes can be dispensed.
WFS_DEP_ENVINOP	The envelope supply unit is in an inoperable state. No envelopes can be dispensed.
WFS_DEP_ENVMISSING	The envelope supply unit is missing.
WFS_DEP_ENVNOTSUPP	The physical device has no envelope supply.
WFS_DEP_ENVUNLOCKED	The envelope supply unit is unlocked.
WFS_DEP_ENVUNKNOWN	Due to a hardware error or other condition, the state of the envelope supply cannot be determined.

*fwEnvDispenser*

Specifies the state of the envelope dispenser. Specified as one of the following flags:

Value	Meaning
WFS_DEP_ENVOK	The envelope dispenser is present and in a good state.
WFS_DEP_ENVINOP	The envelope dispenser is present but in an inoperable state. No envelopes can be dispensed.
WFS_DEP_ENVUNKNOWN	Due to a hardware error or other condition, the state of the envelope dispenser cannot be determined.
WFS_DEP_ENVNOTSUPP	The physical device has no envelope dispenser.

*fwPrinter*

Specifies the state of the printer. Specified as one of the following flags:

Value	Meaning
WFS_DEP_PTROK	The printer is present and in a good state.
WFS_DEP_PTRINOP	The printer is inoperative.
WFS_DEP_PTRUNKNOWN	Due to a hardware error or other condition, the state of the printer cannot be determined.
WFS_DEP_PTRNOTSUPP	The physical device has no printer.

*fwToner*

Specifies the state of the toner (or ink) for the printer. Specified as one of the following flags:

Value	Meaning
WFS_DEP_TONERFULL	The toner cassette is full.
WFS_DEP_TONERLOW	The toner in the printer is low.
WFS_DEP_TONEROUT	The toner in the printer is empty.
WFS_DEP_TONERUNKNOWN	Due to a hardware error or other condition, the state of the toner for the printer cannot be determined.
WFS_DEP_TONERNOTSUPP	The physical device has no toner.

*fwShutter*

Specifies the state of the shutter or door. Specified as one of the following flags:

Value	Meaning
WFS_DEP_SHTCLOSED	The shutter is closed.
WFS_DEP_SHTOPEN	The shutter is open.
WFS_DEP_SHTJAMMED	The shutter is jammed.
WFS_DEP_SHTUNKNOWN	Due to a hardware error or other condition, the state of the shutter cannot be determined.
WFS_DEP_SHTNOTSUPP	The physical device has no shutter.

*wNumOfDeposits*

Specifies the number of envelopes or bags in the deposit container. This value is persistent, i.e. maintained through power failures, opens, closes and system resets.

*lpszExtra*

Pointer to a list of vendor-specific, or any other extended, information. The information is returned as a series of “key=value” strings so that it is easily extensible by Service Providers. Each string is null-terminated, with the final string terminating with two null characters. An empty list may be indicated by either a NULL pointer or a pointer to two consecutive null characters.

*dwGuidLights [...]*

Specifies the state of the guidance light indicators. A number of guidance light types are defined below. Vendor specific guidance lights are defined starting from the end of the array. The maximum guidance light index is WFS\_DEP\_GUIDLIGHTS\_MAX.

Specifies the state of the guidance light indicator as

WFS\_DEP\_GUIDANCE\_NOT\_AVAILABLE, WFS\_DEP\_GUIDANCE\_OFF or a combination of the following flags consisting of one type B, and optionally one type C.

Value	Meaning	Type
WFS_DEP_GUIDANCE_NOT_AVAILABLE	The status is not available.	A
WFS_DEP_GUIDANCE_OFF	The light is turned off.	A
WFS_DEP_GUIDANCE_SLOW_FLASH	The light is blinking slowly.	B
WFS_DEP_GUIDANCE_MEDIUM_FLASH	The light is blinking medium frequency.	B
WFS_DEP_GUIDANCE_QUICK_FLASH	The light is blinking quickly.	B
WFS_DEP_GUIDANCE_CONTINUOUS	The light is turned on continuous (steady).	B
WFS_DEP_GUIDANCE_RED	The light is red.	C
WFS_DEP_GUIDANCE_GREEN	The light is green.	C
WFS_DEP_GUIDANCE_YELLOW	The light is yellow.	C
WFS_DEP_GUIDANCE_BLUE	The light is blue.	C
WFS_DEP_GUIDANCE_CYAN	The light is cyan.	C
WFS_DEP_GUIDANCE_MAGENTA	The light is magenta.	C
WFS_DEP_GUIDANCE_WHITE	The light is white.	C

*dwGuidLights* [WFS\_DEP\_GUIDANCE\_ENVDEPOSITORY]

Specifies the state of the guidance light indicator on the envelope depository unit.

*dwGuidLights* [WFS\_DEP\_GUIDANCE\_ENVDISPENSER]

Specifies the state of the guidance light indicator on the envelope dispenser unit.

*fwDepositLocation*

Specifies the location of the item deposited at the end of the last WFS\_CMD\_DEP\_ENTRY command. Specified as one of the following flags:

Value	Meaning
WFS_DEP_DEPLOCNOTSUPP	Reporting the location of the last deposit is not supported.
WFS_DEP_DEPLOCUNKNOWN	Cannot determine the location of the last deposited item.
WFS_DEP_DEPLOCCONTAINER	The item is in the container.
WFS_DEP_DEPLOCTRANSPORT	The item is in the transport.
WFS_DEP_DEPLOCPRINTER	The item is in the printer.
WFS_DEP_DEPLOCSHUTTER	The item is at the shutter (available for removal).
WFS_DEP_DEPLOCNONE	No item was entered on the last WFS_CMD_DEP_ENTRY.
WFS_DEP_DEPLOCREMOVED	The item was removed.

For devices capable of identifying item location, WFS\_DEP\_DEPLOCNONE is returned when the status is queried before any call to WFS\_CMD\_DEP\_ENTRY.

*wDevicePosition*

Specifies the device position. The device position value is independent of the *fwDevice* value, e.g. when the device position is reported as WFS\_DEP\_DEVICEINPOSITION, *fwDevice* can have any of the values defined above (including WFS\_DEP\_DEVONLINE or WFS\_DEP\_DEVOFFLINE). If the device is not in its normal operating position (i.e. WFS\_DEP\_DEVICEINPOSITION) then media may not be presented through the normal customer interface. This value is one of the following values:

Value	Meaning
WFS_DEP_DEVICEINPOSITION	The device is in its normal operating position, or is fixed in place and cannot be moved.
WFS_DEP_DEVICEINPOSITION	The device has been removed from its normal operating position.
WFS_DEP_DEVICEPOSUNKNOWN	Due to a hardware error or other condition, the position of the device cannot be determined.
WFS_DEP_DEVICEPOSNOTSUPP	The physical device does not have the capability of detecting the position.

*usPowerSaveRecoveryTime*

Specifies the actual number of seconds required by the device to resume its normal operational state from the current power saving mode. This value is zero if either the power saving mode has not been activated or no power save control is supported.

*wAntiFraudModule*

Specifies the state of the anti-fraud module as one of the following values:

Value	Meaning
WFS_DEP_AFMNOTSUPP	No anti-fraud module is available.
WFS_DEP_AFMOK	Anti-fraud module is in a good state and no foreign device is detected.
WFS_DEP_AFMINOP	Anti-fraud module is inoperable.
WFS_DEP_AFMDEVICEDETECTED	Anti-fraud module detected the presence of a foreign device.
WFS_DEP_AFMUNKNOWN	The state of the anti-fraud module cannot be determined.

**Error Codes** Only the generic error codes defined in [Ref. 1] can be generated by this command.

**Comments** Applications which require or expect specific information to be present in the *lpszExtra* parameter may not be device or vendor-independent.

In the case where communications with the device has been lost, the *fwDevice* field will report WFS\_DEP\_DEVPOWEROFF when the device has been removed or WFS\_DEP\_DEVHWERROR if the communications are unexpectedly lost. All other fields should contain a value based on the following rules and priority:

1. Report the value as unknown.
2. Report the value as a general h/w error.
3. Report the value as the last known value.

## 4.2 WFS\_INF\_DEP\_CAPABILITIES

---

**Description** This command is used to retrieve the capabilities of the Depository.

**Input Param** None.

**Output Param** LPWFSDEPCAPS lpCaps;

```
typedef struct _wfs_dep_caps
{
    WORD                wClass;
    WORD                fwType;
    WORD                fwEnvSupply;
    BOOL                bDepTransport;
    BOOL                bPrinter;
    BOOL                bToner;
    BOOL                bShutter;
    BOOL                bPrintOnRetracts;
    WORD                fwRetractEnvelope;
    WORD                wMaxNumChars;
    WORD                fwCharSupport;
    LPSTR               lpszExtra;
    DWORD               dwGuidLights[WFS_DEP_GUIDLIGHTS_SIZE];
    BOOL                bPowerSaveControl;
    BOOL                bAntiFraudModule;
} WFSDEPCAPS, *LPWFSDEPCAPS;
```

*wClass*

Specifies the logical service class as WFS\_SERVICE\_CLASS\_DEP.

*fwType*

Specifies the type of the depository device as a combination of the following flags:

Value	Meaning
WFS_DEP_TYPEENVELOPE	Depository accepts envelopes.
WFS_DEP_TYPEBAGDROP	Depository accepts bags.

*fwEnvSupply*

Defines what type of Envelope Supply Unit exists as one of the following flags:

Value	Meaning
WFS_DEP_ENVMOTORIZED	Envelope Supply can dispense envelopes.
WFS_DEP_ENVMANUAL	Envelope Supply is manual and must be unlocked to allow envelopes to be taken. The Service Event, WFS_SRVE_DEP_ENVTAKEN, can not be sent and the Execute Command, WFS_CMD_DEP_RETRACT can not be supported.
WFS_DEP_ENVNONE	No Envelope Supply or Envelope Supply is manual and envelopes can be taken at any time. The Service Event, WFS_SRVE_DEP_ENVTAKEN, can not be sent and the Execute Command, WFS_CMD_DEP_RETRACT can not be supported.

*bDepTransport*

Specifies whether a deposit transport mechanism is available.

*bPrinter*

Specifies whether a printer is available.

*bToner*

Specifies whether the printer has a toner (or ink) cassette.

*bShutter*

Specifies whether a deposit transport shutter is available.

*bPrintOnRetracts*

Specifies whether the device can print the string specified in the *lpszPrintData* or *lpszUNICODEPrintData* field of the WFS\_CMD\_DEP\_RETRACT command on retracted envelopes.

*fwRetractEnvelope*

Specifies the ability of the envelope dispenser to retract envelopes as one of the following flags:

Value	Meaning
WFS_DEP_NORETRACT	The envelope dispenser does not have the capability to retract envelopes.
WFS_DEP_RETRACTDEP	Retracted envelopes are put in the deposit container.
WFS_DEP_RETRACTDISP	Retracted envelopes are retracted back to the envelope dispenser.

*wMaxNumChars*

Specifies the maximum number of characters that can be printed on the envelope.

*fwCharSupport*

One or more flags specifying the Character Sets supported by the Service Provider:

Value	Meaning
WFS_DEP_ASCII	ASCII is supported for execute command data values.
WFS_DEP_UNICODE	UNICODE is supported for execute command data values.

*lpszExtra*

Pointer to a list of vendor-specific, or any other extended, information. The information is returned as a series of “*key=value*” strings so that it is easily extensible by Service Providers. Each string is null-terminated, with the final string terminating with two null characters. An empty list may be indicated by either a NULL pointer or a pointer to two consecutive null characters.

*dwGuidLights [...]*

Specifies which guidance lights are available. A number of guidance light types are defined below. Vendor specific guidance lights are defined starting from the end of the array. The maximum guidance light index is WFS\_DEP\_GUIDLIGHTS\_MAX.

The elements of this array are specified as a combination of the following flags and indicate all of the possible flash rates (type B) and colors (type C) that the guidance light indicator is capable of handling. If the guidance light indicator only supports one color then no value of type C is returned. A value of WFS\_DEP\_GUIDANCE\_NOT\_AVAILABLE indicates that the device has no guidance light indicator or the device controls the light directly with no application control possible.

Value	Meaning	Type
WFS_DEP_GUIDANCE_NOT_AVAILABLE	There is no guidance light control available at this position.	A
WFS_DEP_GUIDANCE_OFF	The light is turned off.	A
WFS_DEP_GUIDANCE_SLOW_FLASH	The light is blinking slowly.	B
WFS_DEP_GUIDANCE_MEDIUM_FLASH	The light is blinking medium frequency.	B
WFS_DEP_GUIDANCE_QUICK_FLASH	The light is blinking quickly.	B
WFS_DEP_GUIDANCE_CONTINUOUS	The light is turned on continuous (steady).	B
WFS_DEP_GUIDANCE_RED	The light is red.	C
WFS_DEP_GUIDANCE_GREEN	The light is green.	C
WFS_DEP_GUIDANCE_YELLOW	The light is yellow.	C
WFS_DEP_GUIDANCE_BLUE	The light is blue.	C
WFS_DEP_GUIDANCE_CYAN	The light is cyan.	C
WFS_DEP_GUIDANCE_MAGENTA	The light is magenta.	C
WFS_DEP_GUIDANCE_WHITE	The light is white.	C

## CWA 16374-8:2011 (E)

*dwGuidLights* [WFS\_DEP\_GUIDANCE\_ENVDEPOSITORY]

Specifies whether the guidance light indicator on the envelope depository unit is available.

*dwGuidLights* [WFS\_DEP\_GUIDANCE\_ENVDISPENSER]

Specifies whether the guidance light indicator on the envelope dispenser unit is available.

*bPowerSaveControl*

Specifies whether power saving control is available. This can either be TRUE if available or FALSE if not available.

*bAntiFraudModule*

Specifies whether the anti-fraud module is available. This can either be TRUE if available or FALSE if not available.

**Error Codes** Only the generic error codes defined in [Ref. 1] can be generated by this command.

**Comments** Applications which require or expect specific information to be present in the *lpzExtra* parameter may not be device or vendor-independent.

## 5. Execute Commands

---

### 5.1 WFS\_CMD\_DEP\_ENTRY

---

- Description** This command starts the entry of an envelope and attempts to deposit it into the deposit container. The WFS\_EXEE\_DEP\_INSERTDEPOSIT event will be generated when the device is ready to accept the deposit.
- A deposit is considered to be successful if an envelope is inserted and the shutter closes such that the customer no longer has access to it. This includes cases where the deposited envelope reaches the deposit container, becomes jammed before reaching the container, or cannot be returned to the customer.
- If a successful deposit takes place, then this command will always complete with WFS\_SUCCESS, and any errors detected during the operation will be returned by the WFS\_EXEE\_DEP\_DEPOSITERROR event.
- If a successful deposit causes the deposit bin to reach a high or full threshold, a WFS\_USRE\_DEP\_DEPTHRESHOLD event will be sent.
- A deposit is considered to be unsuccessful if an envelope is inserted, an error occurs, and the customer has the ability to access it. This includes cases where an envelope is returned to the user, or cases where it becomes jammed but the customer is still able to access it.
- If an unsuccessful deposit takes place, then the command will always complete with an appropriate error code, and any errors detected during the operation will be returned by the WFS\_EXEE\_DEP\_DEPOSITERROR event.
- If the envelope is entered and then returned to the exit slot for removal by the customer, if the deposit device is capable of this operation (either hardware capability or hardware problems such as a jam may prohibit the envelope from being returned) a WFS\_SRVE\_DEP\_ENVTAKEN will be sent when it is removed.
- For example, if the envelope entered has an incorrect size and the deposit was unsuccessful, the envelope is returned to the exit slot for removal by the customer. If the envelope is returned to the customer for removal, the command will complete with WFS\_ERR\_DEP\_ENVSIZE. A WFS\_SRVE\_DEP\_ENVTAKEN is sent when the envelope is removed. But if returning the envelope is not possible and the customer cannot access the envelope, the command will complete with WFS\_SUCCESS and a WFS\_EXEE\_DEP\_DEPOSITERROR event is sent reporting a WFS\_ERR\_DEP\_ENVSIZE.
- Input Param** LPWFSDEPENVELOPE lpEnvelope;
- ```
typedef struct _wfs_dep_envelope
{
    LPSTR          lpszPrintData;
    LPWSTR         lpszUNICODEPrintData;
} WFSDEPENVELOPE, *LPWFSDEPENVELOPE;
```
- lpszPrintData*  
Specifies the data that will be printed on the envelope that is entered by the customer.
- lpszUNICODEPrintData*  
Specifies the UNICODE data that will be printed on the envelope that is entered by the customer.
- The *lpszUNICODEPrintData* field should only be used if the Service Provider supports UNICODE. The *lpszPrintData* and *lpszUNICODEPrintData* fields are mutually exclusive.
- Output Param** None.
- Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

| Value               | Meaning                        |
|---------------------|--------------------------------|
| WFS_ERR_DEP_DEPFULL | The deposit container is full. |

|                            |                                                                                                                                                                   |
|----------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| WFS_ERR_DEP_DEPJAMMED      | An envelope jam occurred in the deposit transport between the entry slot and the deposit container.                                                               |
| WFS_ERR_DEP_ENVSIZE        | The envelope entered has an incorrect size.                                                                                                                       |
| WFS_ERR_DEP_PTRFAIL        | The printer failed.                                                                                                                                               |
| WFS_ERR_DEP_SHTNOTCLOSED   | The shutter failed to close.                                                                                                                                      |
| WFS_ERR_DEP_SHTNOTOPENED   | The shutter failed to open.                                                                                                                                       |
| WFS_ERR_DEP_CONTMISSING    | The deposit container is not present.                                                                                                                             |
| WFS_ERR_DEP_DEPUNKNOWN     | The result of the deposit is not known.                                                                                                                           |
| WFS_ERR_DEP_CHARSETNOTSUPP | Character set(s) supported by Service Provider is inconsistent with use of <i>lpszPrintData</i> or <i>lpszUNICODEPrintData</i> fields.                            |
| WFS_ERR_DEP_TONEROUT       | Toner or ink supply is empty or printing contrast with ribbon is not sufficient. This error can only occur when a print string was passed in the input parameter. |

**Events** In addition to the generic events defined in [Ref. 1], the following events can be generated by this command:

| Value                       | Meaning                                                                                         |
|-----------------------------|-------------------------------------------------------------------------------------------------|
| WFS_SRVE_DEP_ENVTAKEN       | The envelope has been taken by the user.                                                        |
| WFS_EXEE_DEP_ENVDEPOSITED   | The envelope has been deposited in the deposit container.                                       |
| WFS_EXEE_DEP_DEPOSITERROR   | An error occurred during the deposit operation.                                                 |
| WFS_USRE_DEP_DEPTHRESHOLD   | This user event is used to specify that the state of the deposit container reached a threshold. |
| WFS_USRE_DEP_TONERTHRESHOLD | This user event is used to specify that the state of the toner supply reached a threshold.      |
| WFS_SRVE_DEP_ENVINSERTED    | An envelope has been inserted by the user.                                                      |
| WFS_EXEE_DEP_INSERTDEPOSIT  | Device is ready to accept deposit from the user.                                                |

**Comments** If the data specified in *lpszPrintData* or *lpszUNICODEPrintData* is longer than the maximum allowed characters, the error code WFS\_ERR\_INVALID\_DATA will be returned.

## 5.2 WFS\_CMD\_DEP\_DISPENSE

---

**Description** This command is used to dispense an envelope from the envelope supply. This command will either action the dispensing of an envelope from the envelope supply or will unlock the envelope supply for manual access.

**Input Param** None.

**Output Param** None.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

| Value                    | Meaning                                                                                              |
|--------------------------|------------------------------------------------------------------------------------------------------|
| WFS_ERR_DEP_ENVEMPTY     | There is no envelope in the envelope unit.                                                           |
| WFS_ERR_DEP_ENVJAMMED    | An envelope jam occurred in the dispenser transport between the envelope supply and the output slot. |
| WFS_ERR_DEP_SHTNOTOPENED | The shutter failed to open.                                                                          |

**Events** In addition to the generic events defined in [Ref. 1], the following events can be generated by this command:

| Value                     | Meaning                                                                                       |
|---------------------------|-----------------------------------------------------------------------------------------------|
| WFS_SRVE_DEP_ENVTAKEN     | The envelope has been taken by the user.                                                      |
| WFS_USRE_DEP_ENVTHRESHOLD | This user event is used to specify that the state of the envelope supply reached a threshold. |

**Comments** None.

### 5.3 WFS\_CMD\_DEP\_RETRACT

---

**Description** This command is used to retract an envelope that was not taken by a customer after an envelope dispense operation. The given string is printed on the envelope and the envelope is retracted into the deposit container or back to the envelope dispenser, depending on the capabilities of the physical device. If a retract to the deposit bin causes the deposit bin to reach a high or full threshold, a WFS\_USRE\_DEP\_DEPTHRESHOLD event will be sent.

This command will only return with an error code if the retract has not taken place. The error code will then describe the reason for the failure.

**Input Param** LPWFSDEPENVELOPE lpEnvelope;

```
typedef struct _wfs_dep_envelope
{
    LPSTR                lpzPrintData;
    LPSTR                lpzUNICODEPrintData;
} WFSDEPENVELOPE, *LPWFSDEPENVELOPE;
```

*lpzPrintData*

Specifies the data that will be printed on the envelope that is retracted.

*lpzUNICODEPrintData*

Specifies the UNICODE data that will be printed on the envelope that is retracted.

The *lpzUNICODEPrintData* field should only be used if the Service Provider supports UNICODE. The *lpzPrintData* and *lpzUNICODEPrintData* fields are mutually exclusive.

**Output Param** None.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

| Value                      | Meaning                                                                                                                                                                   |
|----------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| WFS_ERR_DEP_DEPFULL        | The deposit container is full.                                                                                                                                            |
| WFS_ERR_DEP_DEPJAMMED      | An envelope jam occurred in the deposit transport between the entry slot and the deposit container (may only occur with hardware that retracts to the deposit container). |
| WFS_ERR_DEP_ENVJAMMED      | An envelope jam occurred between the entry slot and the envelope container (may only occur with hardware that retracts to the envelope container).                        |
| WFS_ERR_DEP_NOENV          | No envelope to retract.                                                                                                                                                   |
| WFS_ERR_DEP_PTRFAIL        | The printer failed.                                                                                                                                                       |
| WFS_ERR_DEP_SHTNOTCLOSED   | The shutter failed to close.                                                                                                                                              |
| WFS_ERR_DEP_CONTMISSING    | The deposit container is not present.                                                                                                                                     |
| WFS_ERR_DEP_CHARSETNOTSUPP | Character set(s) supported by Service Provider is inconsistent with use of <i>lpzPrintData</i> or <i>lpzUNICODEPrintData</i> fields.                                      |
| WFS_ERR_DEP_TONEROUT       | Toner or ink supply is empty or printing contrast with ribbon is not sufficient.                                                                                          |

**Events** In addition to the generic events defined in [Ref. 1], the following events can be generated by this command:

| Value                       | Meaning                                                                                         |
|-----------------------------|-------------------------------------------------------------------------------------------------|
| WFS_USRE_DEP_DEPTHRESHOLD   | This user event is used to specify that the state of the deposit container reached a threshold. |
| WFS_USRE_DEP_TONERTHRESHOLD | This user event is used to specify that the state of the toner supply reached a threshold.      |
| WFS_SRVE_DEP_ENVTAKEN       | The envelope has been taken by the user.                                                        |

**Comments** If the data specified in *lpzPrintData* or *lpzUNICODEPrintData* is longer than the maximum

allowed characters, the error code WFS\_ERR\_INVALID\_DATA will be returned.

### 5.4 WFS\_CMD\_DEP\_RESET\_COUNT

---

| <b>Description</b>        | This command is used to reset the present value for number of envelopes/bags in the deposit container to zero.                                                                                                                                        |              |                |                           |                                                                                                 |
|---------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------|----------------|---------------------------|-------------------------------------------------------------------------------------------------|
| <b>Input Param</b>        | None.                                                                                                                                                                                                                                                 |              |                |                           |                                                                                                 |
| <b>Output Param</b>       | None.                                                                                                                                                                                                                                                 |              |                |                           |                                                                                                 |
| <b>Error Codes</b>        | Only the generic error codes defined in [Ref. 1] can be generated by this command.                                                                                                                                                                    |              |                |                           |                                                                                                 |
| <b>Events</b>             | In addition to the generic events defined in [Ref. 1], the following events can be generated by this command:                                                                                                                                         |              |                |                           |                                                                                                 |
|                           | <table><thead><tr><th><u>Value</u></th><th><u>Meaning</u></th></tr></thead><tbody><tr><td>WFS_USRE_DEP_DEPTHRESHOLD</td><td>This user event is used to specify that the state of the deposit container reached a threshold.</td></tr></tbody></table> | <u>Value</u> | <u>Meaning</u> | WFS_USRE_DEP_DEPTHRESHOLD | This user event is used to specify that the state of the deposit container reached a threshold. |
| <u>Value</u>              | <u>Meaning</u>                                                                                                                                                                                                                                        |              |                |                           |                                                                                                 |
| WFS_USRE_DEP_DEPTHRESHOLD | This user event is used to specify that the state of the deposit container reached a threshold.                                                                                                                                                       |              |                |                           |                                                                                                 |
| <b>Comments</b>           | None.                                                                                                                                                                                                                                                 |              |                |                           |                                                                                                 |

## 5.5 WFS\_CMD\_DEP\_RESET

---

**Description** Sends a service reset to the Service Provider. The Service Provider may reset the deposit device and also the envelope dispenser, if possible. Any media found in the device can be either captured or completely ejected (depending on hardware). If a capture into the deposit bin causes the deposit bin to reach a high or full threshold, a WFS\_USRE\_DEP\_DEPTHTHRESHOLD event will be sent. If the WFS\_CMD\_DEP\_RESET command is requested to eject the media and the hardware is not capable of this operation either due to hardware capability or hardware error such as a jam, the Service Provider will retract the media in order to attempt to make the device operational. The WFS\_SRVE\_DEP\_MEDIADETECTED event will indicate the position of the detected media following completion of the command. If the input parameter to the WFS\_CMD\_DEP\_RESET command is NULL, the Service Provider will go through default actions to clear the deposit transport. The WFS\_SRVE\_DEP\_MEDIADETECTED event will indicate the position of any detected media following completion of the command. The envelope dispenser will go through the most effective means to clear any jammed media.

**Input Param** LPDWORD *lpdwDepMediaControl*;

Specifies the action that should be done if deposited media is detected during the reset operation, as one of the following values:

| Value               | Meaning                                                                                                     |
|---------------------|-------------------------------------------------------------------------------------------------------------|
| WFS_DEP_CTRLREJECT  | Any media detected in the device should be completely ejected (depending on the hardware).                  |
| WFS_DEP_CTRLRETRACT | Any media detected in the device should be deposited into the deposit container during the reset operation. |

If *lpdwDepMediaControl* is set to NULL, the Service Provider will go through default actions to clear the deposit transport.

**Output Param** None.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

| Value                    | Meaning                                                                                              |
|--------------------------|------------------------------------------------------------------------------------------------------|
| WFS_ERR_DEP_DEPFULL      | The deposit container is full.                                                                       |
| WFS_ERR_DEP_DEPJAMMED    | An envelope jam occurred in the deposit transport.                                                   |
| WFS_ERR_DEP_ENVJAMMED    | An envelope jam occurred in the dispenser transport between the envelope supply and the output slot. |
| WFS_ERR_DEP_SHTNOTOPENED | The shutter failed to open.                                                                          |
| WFS_ERR_DEP_SHTNOTCLOSED | The shutter failed to close.                                                                         |
| WFS_ERR_DEP_CONTMISSING  | The deposit container is not present.                                                                |

**Events** In addition to the generic events defined in [Ref. 1], the following events may be generated by this command, if the appropriate situation occurs and the device service has the capability to detect the situation:

| Value                       | Meaning                                                                                         |
|-----------------------------|-------------------------------------------------------------------------------------------------|
| WFS_SRVE_DEP_ENVTAKEN       | The envelope has been taken by the user.                                                        |
| WFS_USRE_DEP_DEPTHTHRESHOLD | This user event is used to specify that the state of the deposit container reached a threshold. |
| WFS_SRVE_DEP_MEDIADETECTED  | Media is detected in the device during a reset operation.                                       |

**Comments** This command is used by an application control program to cause a device to reset itself to a known good condition. Persistent values may change, but will not be reset as a result of this command (i.e. if an envelope is captured, the *wNumOfDeposits* value in the WFSDEPSTATUS structure will be incremented, but never reset to zero).

## 5.6 WFS\_CMD\_DEP\_SET\_GUIDANCE\_LIGHT

---

**Description** This command is used to set the status of the DEP guidance lights. This includes defining the flash rate and the color. When an application tries to use a color that is not supported then the Service Provider will return the generic error WFS\_ERR\_UNSUPP\_DATA.

**Input Param** LPWFSDEPSETGUIDLIGHT lpSetGuidLight;

```
typedef struct _wfs_dep_set_guidlight
{
    WORD                wGuidLight;
    DWORD               dwCommand;
} WFSDEPSETGUIDLIGHT, *LPWFSDEPSETGUIDLIGHT;
```

*wGuidLight*

Specifies the index of the guidance light to set as one of the values defined within the capabilities section.

*dwCommand*

Specifies the state of the guidance light indicator as WFS\_DEP\_GUIDANCE\_OFF or a combination of the following flags consisting of one type B, and optionally one type C. If no value of type C is specified then the default color is used. The Service Provider determines which color is used as the default color.

| Value                         | Meaning                                                 | Type |
|-------------------------------|---------------------------------------------------------|------|
| WFS_DEP_GUIDANCE_OFF          | The light indicator is turned off.                      | A    |
| WFS_DEP_GUIDANCE_SLOW_FLASH   | The light indicator is set to flash slowly.             | B    |
| WFS_DEP_GUIDANCE_MEDIUM_FLASH | The light indicator is set to flash medium frequency.   | B    |
| WFS_DEP_GUIDANCE_QUICK_FLASH  | The light indicator is set to flash quickly.            | B    |
| WFS_DEP_GUIDANCE_CONTINUOUS   | The light indicator is turned on continuously (steady). | B    |
| WFS_DEP_GUIDANCE_RED          | The light indicator color is set to red.                | C    |
| WFS_DEP_GUIDANCE_GREEN        | The light indicator color is set to green.              | C    |
| WFS_DEP_GUIDANCE_YELLOW       | The light indicator color is set to yellow.             | C    |
| WFS_DEP_GUIDANCE_BLUE         | The light indicator color is set to blue.               | C    |
| WFS_DEP_GUIDANCE_CYAN         | The light indicator color is set to cyan.               | C    |
| WFS_DEP_GUIDANCE_MAGENTA      | The light indicator color is set to magenta.            | C    |
| WFS_DEP_GUIDANCE_WHITE        | The light indicator color is set to white.              | C    |

**Output Param** None.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

| Value                    | Meaning                                                                                                  |
|--------------------------|----------------------------------------------------------------------------------------------------------|
| WFS_ERR_DEP_INVALID_PORT | An attempt to set a guidance light to a new value was invalid because the guidance light does not exist. |

**Events** Only the generic events defined in [Ref. 1] can be generated by this command.

**Comments** Guidance light support was added into the DEP primarily to support guidance lights for workstations where more than one instance of a DEP is present. The original SIU guidance light mechanism was not able to manage guidance lights for workstations with multiple DEPs. This command can also be used to set the status of the DEP guidance lights when only one instance of a DEP is present.

The slow and medium flash rates must not be greater than 2.0 Hz. It should be noted that in order to comply with American Disabilities Act guidelines only a slow or medium flash rate must be used.

## 5.7 WFS\_CMD\_DEP\_SUPPLY\_REPLENISH

---

**Description** After the supplies have been replenished, this command is used to indicate that the specified supplies have been replenished and are expected to be in a healthy state.

Hardware that cannot detect the level of a supply and reports on the supply's status using metrics (or some other means), must assume the supply has been fully replenished after this command is issued. The appropriate threshold event must be broadcast.

Hardware that can detect the level of a supply must update its status based on its sensors, generate a threshold event if appropriate and succeed the command even if the supply has not been replenished. If it has already detected the level and reported the threshold before this command was issued, the command must succeed and no threshold event is required.

**Input Param** LPWFSDEPSUPPLYREPLEN lpSupplyReplen;

```
typedef struct _wfs_dep_supply_replen
{
    WORD                fwSupplyReplen;
} WFSDEPSUPPLYREPLEN, *LPWFSDEPSUPPLYREPLEN;
```

*fwSupplyReplen*

Specifies the supply that was replenished as a combination of the following values:

| Value                | Meaning                              |
|----------------------|--------------------------------------|
| WFS_DEP_REPLEN_ENV   | The envelope supply was replenished. |
| WFS_DEP_REPLEN_TONER | The toner supply was replenished.    |

**Output Param** None.

**Error Codes** Only the generic error codes defined in [Ref. 1] can be generated by this command.

**Events** In addition to the generic events defined in [Ref. 1], the following events can be generated by this command:

| Value                       | Meaning                                                                                                                                    |
|-----------------------------|--------------------------------------------------------------------------------------------------------------------------------------------|
| WFS_USRE_DEP_ENVTHRESHOLD   | This user event is used to specify that the state of the envelope supply threshold has been cleared.                                       |
| WFS_USRE_DEP_TONERTHRESHOLD | This user event is used to specify that the state of the toner (or ink supply or the state of a ribbon) supply threshold has been cleared. |

**Comments** If any one of the specified supplies is not supported by a Service Provider, WFS\_ERR\_UNSUPP\_DATA should be returned, and no replenishment actions will be taken by the Service Provider.

## 5.8 WFS\_CMD\_DEP\_POWER\_SAVE\_CONTROL

---

**Description** This command activates or deactivates the power-saving mode.

If the Service Provider receives another execute command while in power saving mode, the Service Provider automatically exits the power saving mode, and executes the requested command. If the Service Provider receives an information command while in power saving mode, the Service Provider will not exit the power saving mode.

**Input Param** LPWFSDEPPOWERSAVECONTROL lpPowerSaveControl;

```
typedef struct _wfs_dep_power_save_control
{
    USHORT                usMaxPowerSaveRecoveryTime;
} WFSDEPPOWERSAVECONTROL, *LPWFSDEPPOWERSAVECONTROL;
```

*usMaxPowerSaveRecoveryTime*

Specifies the maximum number of seconds in which the device must be able to return to its normal operating state when exiting power save mode. The device will be set to the highest possible power save mode within this constraint. If *usMaxPowerSaveRecoveryTime* is set to zero then the device will exit the power saving mode.

**Output Param** None.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

| Value                             | Meaning                                                                                                                                                                        |
|-----------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| WFS_ERR_DEP_POWERSAVETOOSHORT     | The power saving mode has not been activated because the device is not able to resume from the power saving mode within the specified <i>usMaxPowerSaveRecoveryTime</i> value. |
| WFS_ERR_DEP_POWERSAVEMEDIAPRESENT | The power saving mode has not been activated because media is present inside the device.                                                                                       |

**Events** In addition to the generic events defined in [Ref. 1], the following events can be generated by this command:

| Value                          | Meaning                                   |
|--------------------------------|-------------------------------------------|
| WFS_SRVE_DEP_POWER_SAVE_CHANGE | The power save recovery time has changed. |

**Comments** None.

## 6. Events

---

### 6.1 WFS\_SRVE\_DEP\_ENVTAKEN

---

|                    |                                                                                         |
|--------------------|-----------------------------------------------------------------------------------------|
| <b>Description</b> | This service event is used to specify that the envelope has been taken by the customer. |
| <b>Event Param</b> | None.                                                                                   |
| <b>Comments</b>    | None.                                                                                   |

## 6.2 WFS\_EXEE\_DEP\_ENVDEPOSITED

---

|                    |                                                                                                      |
|--------------------|------------------------------------------------------------------------------------------------------|
| <b>Description</b> | This execute event is used to specify that the envelope has been deposited in the deposit container. |
| <b>Event Param</b> | None.                                                                                                |
| <b>Comments</b>    | None.                                                                                                |

### 6.3 WFS\_EXEE\_DEP\_DEPOSITERROR

---

|                    |                                                                                                                                                               |
|--------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>Description</b> | This execute event is used to specify that an error occurred during the deposit operation. For every error that occurred a single execute event is generated. |
| <b>Event Param</b> | LPLONG <i>lplError</i> ;<br><br><i>lplError</i><br>For a list of possible error conditions see the description of the WFS_CMD_DEP_ENTRY command.              |
| <b>Comments</b>    | None.                                                                                                                                                         |

## 6.4 WFS\_USRE\_DEP\_DEPTHRESHOLD

---

**Description** This user event is used to specify that the state of the deposit container reached a threshold.

**Event Param** LPWORD lpwDepositThreshold;

*lpwDepositThreshold*

Specified as one of the following flags:

| Value           | Meaning                                           |
|-----------------|---------------------------------------------------|
| WFS_DEP_DEPOK   | The deposit container is in a good state.         |
| WFS_DEP_DEPHIGH | The deposit container is almost full (threshold). |
| WFS_DEP_DEPFULL | The deposit container is full.                    |

**Comments** None.

## 6.5 WFS\_USRE\_DEP\_TONERTHRESHOLD

---

**Description** This user event is used to specify that the state of the toner (or ink supply or the state of a ribbon) reached a threshold.

**Event Param** LPWORD lpwTonerThreshold;  
*lpwTonerThreshold*  
 Specified as one of the following flags:

| Value             | Meaning                                                                                          |
|-------------------|--------------------------------------------------------------------------------------------------|
| WFS_DEP_TONERFULL | The toner or ink supply is full or the ribbon is OK.                                             |
| WFS_DEP_TONERLOW  | The toner or ink supply is low or the print contrast with a ribbon is weak.                      |
| WFS_DEP_TONEROUT  | The toner or ink supply is empty or the print contrast with a ribbon is not sufficient any more. |

**Comments** None.

## 6.6 WFS\_USRE\_DEP\_ENVTHRESHOLD

---

**Description** This user event is used to specify that the state of the envelope supply reached a threshold.

**Event Param** LPWORD lpwEnvelopeThreshold;

*lpwEnvelopeThreshold*

Specified as one of the following flags:

| Value            | Meaning                                                                     |
|------------------|-----------------------------------------------------------------------------|
| WFS_DEP_ENVOK    | The envelope supply is present and in a good state.                         |
| WFS_DEP_ENVLOW   | The envelope supply is present but low.                                     |
| WFS_DEP_ENVEMPTY | The envelope supply is present but empty.<br>No envelopes can be dispensed. |

**Comments** None.

## 6.7 WFS\_SRVE\_DEP\_CONTINSERTED

---

|                    |                                                                                                       |
|--------------------|-------------------------------------------------------------------------------------------------------|
| <b>Description</b> | This service event is used to specify that the deposit container has been reinserted into the device. |
| <b>Event Param</b> | None.                                                                                                 |
| <b>Comments</b>    | None.                                                                                                 |

## 6.8 WFS\_SRVE\_DEP\_CONTREMOVED

---

|                    |                                                                                                    |
|--------------------|----------------------------------------------------------------------------------------------------|
| <b>Description</b> | This service event is used to specify that the deposit container has been removed from the device. |
| <b>Event Param</b> | None.                                                                                              |
| <b>Comments</b>    | None.                                                                                              |

## 6.9 WFS\_SRVE\_DEP\_ENVINSERTED

---

|                    |                                                                                           |
|--------------------|-------------------------------------------------------------------------------------------|
| <b>Description</b> | This service event is used to specify that an envelope has been inserted by the customer. |
| <b>Event Param</b> | None.                                                                                     |
| <b>Comments</b>    | None.                                                                                     |

## 6.10 WFS\_SRVE\_DEP\_MEDIADETECTED

---

**Description** This event is generated when media is detected in the device during a reset operation. The media may be detected as a result of the reset operation on the envelope dispenser, the envelope depositor, or both.

**Event Param** LPWFSDEPMEDIADETECTED lpMediaDetected;

```
typedef struct _wfs_dep_media_detected
{
    WORD                wDispenseMedia;
    WORD                wDepositMedia;
} WFSDEPMEDIADETECTED, *LPWFSDEPMEDIADETECTED;
```

*wDispenseMedia*

Specifies the dispensed envelope position after the reset operation, as one of the following values:

| Value                  | Meaning                                                                         |
|------------------------|---------------------------------------------------------------------------------|
| WFS_DEP_NOMEDIA        | No dispensed media was detected during the reset operation.                     |
| WFS_DEP_MEDIARETRACTED | The media was retracted into the deposit container during the reset operation.  |
| WFS_DEP_MEDIADISPENSER | The media was retracted into the envelope dispenser during the reset operation. |
| WFS_DEP_MEDIAEJECTED   | The media is in the exit slot.                                                  |
| WFS_DEP_MEDIAJAMMED    | The media is jammed in the device.                                              |
| WFS_DEP_MEDIAUNKNOWN   | The media is in an unknown position.                                            |

*wDepositMedia*

Specifies the deposited media position after the reset operation, as one of the following values:

| Value                  | Meaning                                                                        |
|------------------------|--------------------------------------------------------------------------------|
| WFS_DEP_NOMEDIA        | No deposited media was detected during the reset operation.                    |
| WFS_DEP_MEDIARETRACTED | The media was retracted into the deposit container during the reset operation. |
| WFS_DEP_MEDIAEJECTED   | The media is in the exit slot.                                                 |
| WFS_DEP_MEDIAJAMMED    | The media is jammed in the device.                                             |
| WFS_DEP_MEDIAUNKNOWN   | The media is in an unknown position.                                           |

**Comments** None.

## 6.11 WFS\_EXEE\_DEP\_INSERTDEPOSIT

---

|                    |                                                                                                                         |
|--------------------|-------------------------------------------------------------------------------------------------------------------------|
| <b>Description</b> | This event notifies the application when the device is ready for the user to make the deposit. This event is mandatory. |
| <b>Event Param</b> | None.                                                                                                                   |
| <b>Comments</b>    | None.                                                                                                                   |

## 6.12 WFS\_SRVE\_DEP\_DEVICEPOSITION

---

**Description** This service event reports that the device has changed its position status.

**Event Param** LPWFSDEPDEVICEPOSITION lpDevicePosition;

```
typedef struct _wfs_dep_device_position
{
    WORD                wPosition;
} WFSDEPDEVICEPOSITION, *LPWFSDEPDEVICEPOSITION;
```

*wPosition*

Position of the device as one of the following values:

| Value                       | Meaning                                                         |
|-----------------------------|-----------------------------------------------------------------|
| WFS_DEP_DEVICEINPOSITION    | The device is in its normal operating position.                 |
| WFS_DEP_DEVICENOTINPOSITION | The device has been removed from its normal operating position. |
| WFS_DEP_DEVICEPOSUNKNOWN    | The position of the device cannot be determined.                |

**Comments** None.

## 6.13 WFS\_SRVE\_DEP\_POWER\_SAVE\_CHANGE

---

**Description** This service event specifies that the power save recovery time has changed.

**Event Param** LPWFSDEPPOWERSAVECHANGE lpPowerSaveChange;

```
typedef struct _wfs_dep_power_save_change
{
    USHORT                usPowerSaveRecoveryTime;
} WFSDEPPOWERSAVECHANGE, *LPWFSDEPPOWERSAVECHANGE;
```

*usPowerSaveRecoveryTime*

Specifies the actual number of seconds required by the device to resume its normal operational state. This value is zero if the device exited the power saving mode.

**Comments** If another device class compounded with this device enters into a power saving mode, this device will automatically enter into the same power saving mode and this event will be generated.

## 7. C - Header file

```

/*****
*
* xfsdep.h   XFS - Depository (DEP) definitions
*
*           Version 3.20   (March 02 2011)
*
*****/

#ifndef __INC_XFSDEP__H
#define __INC_XFSDEP__H

#ifdef __cplusplus
extern "C" {
#endif

#include <xfsapi.h>

/* be aware of alignment */
#pragma pack(push,1)

/* values of WFSDEPCAPS.wClass */

#define      WFS_SERVICE_CLASS_DEP                (6)
#define      WFS_SERVICE_CLASS_VERSION_DEP      (0x1403) /* Version 3.20 */
#define      WFS_SERVICE_CLASS_NAME_DEP        "DEP"

#define      DEP_SERVICE_OFFSET                 (WFS_SERVICE_CLASS_DEP * 100)

/* DEP Info Commands */

#define      WFS_INF_DEP_STATUS                 (DEP_SERVICE_OFFSET + 1)
#define      WFS_INF_DEP_CAPABILITIES          (DEP_SERVICE_OFFSET + 2)

/* DEP Execute Commands */

#define      WFS_CMD_DEP_ENTRY                 (DEP_SERVICE_OFFSET + 1)
#define      WFS_CMD_DEP_DISPENSE              (DEP_SERVICE_OFFSET + 2)
#define      WFS_CMD_DEP_RETRACT               (DEP_SERVICE_OFFSET + 3)
#define      WFS_CMD_DEP_RESET_COUNT           (DEP_SERVICE_OFFSET + 5)
#define      WFS_CMD_DEP_RESET                 (DEP_SERVICE_OFFSET + 6)
#define      WFS_CMD_DEP_SET_GUIDANCE_LIGHT    (DEP_SERVICE_OFFSET + 7)
#define      WFS_CMD_DEP_SUPPLY_REPLENISH      (DEP_SERVICE_OFFSET + 8)
#define      WFS_CMD_DEP_POWER_SAVE_CONTROL    (DEP_SERVICE_OFFSET + 9)

/* DEP Messages */

#define      WFS_SRVE_DEP_ENVTAKEN              (DEP_SERVICE_OFFSET + 1)
#define      WFS_EXEE_DEP_ENVDEPOSITED         (DEP_SERVICE_OFFSET + 2)
#define      WFS_EXEE_DEP_DEPOSITERROR         (DEP_SERVICE_OFFSET + 3)
#define      WFS_USRE_DEP_DEPTHTHRESHOLD      (DEP_SERVICE_OFFSET + 4)
#define      WFS_USRE_DEP_TONERTHRESHOLD      (DEP_SERVICE_OFFSET + 5)
#define      WFS_USRE_DEP_ENVTHRESHOLD        (DEP_SERVICE_OFFSET + 6)
#define      WFS_SRVE_DEP_CONTINSERTED         (DEP_SERVICE_OFFSET + 7)
#define      WFS_SRVE_DEP_CONTRERMOVED        (DEP_SERVICE_OFFSET + 8)
#define      WFS_SRVE_DEP_ENVINSERTED         (DEP_SERVICE_OFFSET + 9)
#define      WFS_SRVE_DEP_MEDIADETECTED       (DEP_SERVICE_OFFSET + 10)
#define      WFS_EXEE_DEP_INSERTDEPOSIT       (DEP_SERVICE_OFFSET + 11)
#define      WFS_SRVE_DEP_DEVICEPOSITION      (DEP_SERVICE_OFFSET + 12)
#define      WFS_SRVE_DEP_POWER_SAVE_CHANGE    (DEP_SERVICE_OFFSET + 13)

/* values of WFSDEPSTATUS.fwDevice */

#define      WFS_DEP_DEVONLINE                 WFS_STAT_DEVONLINE
#define      WFS_DEP_DEVOFFLINE               WFS_STAT_DEVOFFLINE
#define      WFS_DEP_DEVPOWEROFF              WFS_STAT_DEVPOWEROFF
#define      WFS_DEP_DEVBUSY                   WFS_STAT_DEVBUSY
#define      WFS_DEP_DEVNODEVICE              WFS_STAT_DEVNODEVICE

```

## CWA 16374-8:2011 (E)

```
#define WFS_DEP_DEVHWERROR WFS_STAT_DEVHWERROR
#define WFS_DEP_DEVUSERERROR WFS_STAT_DEVUSERERROR
#define WFS_DEP_DEVFRAUDATTEMPT WFS_STAT_DEVFRAUDATTEMPT
#define WFS_DEP_DEVPOTENTIALFRAUD WFS_STAT_DEVPOTENTIALFRAUD

/* values of WFSDEPSTATUS.fwDepContainer, fwDepTransport */

#define WFS_DEP_DEPOK (0)
#define WFS_DEP_DEPHIGH (1)
#define WFS_DEP_DEPFULL (2)
#define WFS_DEP_DEPINOP (3)
#define WFS_DEP_DEPMISSING (4)
#define WFS_DEP_DEPUNKNOWN (5)
#define WFS_DEP_DEPNOTSUPP (6)

/* values of WFSDEPSTATUS.fwEnvSupply, fwEnvDispenser */

#define WFS_DEP_ENVOK (0)
#define WFS_DEP_ENVLOW (1)
#define WFS_DEP_ENVEMPTY (2)
#define WFS_DEP_ENVINOP (3)
#define WFS_DEP_ENVMISSING (4)
#define WFS_DEP_ENVUNKNOWN (5)
#define WFS_DEP_ENVNOTSUPP (6)
#define WFS_DEP_ENVUNLOCKED (7)

/* values of WFSDEPSTATUS.fwPrinter */

#define WFS_DEP_PTROK (0)
#define WFS_DEP_PTRINOP (1)
#define WFS_DEP_PTRUNKNOWN (2)
#define WFS_DEP_PTRNOTSUPP (3)

/* values of WFSDEPSTATUS.fwToner */

#define WFS_DEP_TONERFULL (0)
#define WFS_DEP_TONERLOW (1)
#define WFS_DEP_TONEROUT (2)
#define WFS_DEP_TONERUNKNOWN (3)
#define WFS_DEP_TONERNOTSUPP (4)

/* values of WFSDEPSTATUS.fwShutter */

#define WFS_DEP_SHTCLOSED (0)
#define WFS_DEP_SHTOPEN (1)
#define WFS_DEP_SHTJAMMED (2)
#define WFS_DEP_SHTUNKNOWN (3)
#define WFS_DEP_SHTNOTSUPP (4)

/* Size and max index of dwGuidLights array */

#define WFS_DEP_GUIDLIGHTS_SIZE (32)
#define WFS_DEP_GUIDLIGHTS_MAX (WFS_DEP_GUIDLIGHTS_SIZE - 1)

/* Indices of WFSDEPSTATUS.dwGuidLights [...]
   WFSDEPCAPS.dwGuidLights [...]
*/

#define WFS_DEP_GUIDANCE_ENVDEPOSITORY (0)
#define WFS_DEP_GUIDANCE_ENVDISPENSER (1)

/* Values of WFSDEPSTATUS.dwGuidLights [...]
   WFSDEPCAPS.dwGuidLights [...] */

#define WFS_DEP_GUIDANCE_NOT_AVAILABLE (0x00000000)
#define WFS_DEP_GUIDANCE_OFF (0x00000001)
#define WFS_DEP_GUIDANCE_SLOW_FLASH (0x00000004)
#define WFS_DEP_GUIDANCE_MEDIUM_FLASH (0x00000008)
#define WFS_DEP_GUIDANCE_QUICK_FLASH (0x00000010)
#define WFS_DEP_GUIDANCE_CONTINUOUS (0x00000080)
```

```

#define      WFS_DEP_GUIDANCE_RED                (0x00000100)
#define      WFS_DEP_GUIDANCE_GREEN             (0x00000200)
#define      WFS_DEP_GUIDANCE_YELLOW           (0x00000400)
#define      WFS_DEP_GUIDANCE_BLUE             (0x00000800)
#define      WFS_DEP_GUIDANCE_CYAN             (0x00001000)
#define      WFS_DEP_GUIDANCE_MAGENTA          (0x00002000)
#define      WFS_DEP_GUIDANCE_WHITE            (0x00004000)

/* values of WFSDEPSTATUS.fwDepositLocation */

#define WFS_DEP_DEPLOCNOTSUPP                    (0)
#define WFS_DEP_DEPLOCUNKNOWN                    (1)
#define WFS_DEP_DEPLOCCONTAINER                  (2)
#define WFS_DEP_DEPLOCTRANSPORT                  (3)
#define WFS_DEP_DEPLOCPRINTER                    (4)
#define WFS_DEP_DEPLOCSHUTTER                    (5)
#define WFS_DEP_DEPLOCNONE                        (6)
#define WFS_DEP_DEPLOCREMOVED                    (7)

/* values of WFSDEPSTATUS.wDevicePosition
   WFSDEPDEVICEPOSITION.wPosition */

#define      WFS_DEP_DEVICEINPOSITION            (0)
#define      WFS_DEP_DEVICENOTINPOSITION        (1)
#define      WFS_DEP_DEVICEPOSUNKNOWN           (2)
#define      WFS_DEP_DEVICEPOSNOTSUPP           (3)

/* values of WFSDEPCAPS.fwType */

#define      WFS_DEP_TYPEENVELOPE                (0x0001)
#define      WFS_DEP_TYPEBAGDROP                (0x0002)

/* values of WFSDEPCAPS.fwEnvSupply */

#define      WFS_DEP_ENVMOTORIZED                (1)
#define      WFS_DEP_ENVMANUAL                  (2)
#define      WFS_DEP_ENVNONE                    (3)

/* values of WFSDEPCAPS.fwRetractEnvelope */

#define      WFS_DEP_NORETRACT                    (1)
#define      WFS_DEP_RETRACTDEP                  (2)
#define      WFS_DEP_RETRACTDISP                 (3)

/* values of WFSDEPCAPS.fwCharSupport, WFSDEPENVELOPE.fwCharSupport */

#define      WFS_DEP_ASCII                        (0x0001)
#define      WFS_DEP_UNICODE                     (0x0002)

/* values of dwDepMediaControl */

#define      WFS_DEP_CTRLREJECT                  (0x0001)
#define      WFS_DEP_CTRLRETRACT                 (0x0002)

/* values of WFSDEPMEDIADETECTED.wDispenseMedia, wDepositMedia */

#define      WFS_DEP_NOMEDIA                      (1)
#define      WFS_DEP_MEDIARETRACTED              (2)
#define      WFS_DEP_MEDIADISPENSER              (3)
#define      WFS_DEP_MEDIAEJECTED                (4)
#define      WFS_DEP_MEDIAJAMMED                 (5)
#define      WFS_DEP_MEDIAUNKNOWN                (6)

/* values of WFSDEPSUPPLYREPLEN.fwSupplyReplen */

#define      WFS_DEP_REPLEN_ENV                  (0x0001)
#define      WFS_DEP_REPLEN_TONER                (0x0002)

/* values of WFSDEPSTATUS.wAntiFraudModule */

```

## CWA 16374-8:2011 (E)

```
#define WFS_DEP_AFMNOTSUPP (0)
#define WFS_DEP_AFMOK (1)
#define WFS_DEP_AFMINOP (2)
#define WFS_DEP_AFMDEVICEDETECTED (3)
#define WFS_DEP_AFMUNKNOWN (4)

#define WFS_ERR_DEP_DEPFULL (-(DEP_SERVICE_OFFSET + 0))
#define WFS_ERR_DEP_DEPJAMMED (-(DEP_SERVICE_OFFSET + 1))
#define WFS_ERR_DEP_ENVEMPTY (-(DEP_SERVICE_OFFSET + 2))
#define WFS_ERR_DEP_ENVJAMMED (-(DEP_SERVICE_OFFSET + 3))
#define WFS_ERR_DEP_ENVSIZE (-(DEP_SERVICE_OFFSET + 4))
#define WFS_ERR_DEP_NOENV (-(DEP_SERVICE_OFFSET + 5))
#define WFS_ERR_DEP_PTRFAIL (-(DEP_SERVICE_OFFSET + 6))
#define WFS_ERR_DEP_SHTNOTCLOSED (-(DEP_SERVICE_OFFSET + 7))
#define WFS_ERR_DEP_SHTNOTOPENED (-(DEP_SERVICE_OFFSET + 8))
#define WFS_ERR_DEP_CONTMISSING (-(DEP_SERVICE_OFFSET + 9))
#define WFS_ERR_DEP_DEPUNKNOWN (-(DEP_SERVICE_OFFSET + 10))
#define WFS_ERR_DEP_CHARSETNOTSUPP (-(DEP_SERVICE_OFFSET + 11))
#define WFS_ERR_DEP_TONEROUT (-(DEP_SERVICE_OFFSET + 12))
#define WFS_ERR_DEP_INVALID_PORT (-(DEP_SERVICE_OFFSET + 13))
#define WFS_ERR_DEP_POWERSAVETOOSHORT (-(DEP_SERVICE_OFFSET + 14))
#define WFS_ERR_DEP_POWERSAVEMEDIAPRESENT (-(DEP_SERVICE_OFFSET + 15))

/*=====*/
/* DEP Info Command Structures and variables */
/*=====*/

typedef struct _wfs_dep_status
{
    WORD fwDevice;
    WORD fwDepContainer;
    WORD fwDepTransport;
    WORD fwEnvSupply;
    WORD fwEnvDispenser;
    WORD fwPrinter;
    WORD fwToner;
    WORD fwShutter;
    WORD wNumOfDeposits;
    LPSTR lpszExtra;
    DWORD dwGuidLights[WFS_DEP_GUIDLIGHTS_SIZE];
    WORD fwDepositLocation;
    WORD wDevicePosition;
    USHORT usPowerSaveRecoveryTime;
    WORD wAntiFraudModule;
} WFSDEPSTATUS, *LPWFSDEPSTATUS;

typedef struct _wfs_dep_caps
{
    WORD wClass;
    WORD fwType;
    WORD fwEnvSupply;
    BOOL bDepTransport;
    BOOL bPrinter;
    BOOL bToner;
    BOOL bShutter;
    BOOL bPrintOnRetracts;
    WORD fwRetractEnvelope;
    WORD wMaxNumChars;
    WORD fwCharSupport;
    LPSTR lpszExtra;
    DWORD dwGuidLights[WFS_DEP_GUIDLIGHTS_SIZE];
    BOOL bPowerSaveControl;
    BOOL bAntiFraudModule;
} WFSDEPCAPS, *LPWFSDEPCAPS;

/*=====*/
/* DEP Execute Command Structures */
/*=====*/
```

```

typedef struct _wfs_dep_envelope
{
    LPSTR          lpszPrintData;
    LPWSTR         lpszUNICODEPrintData;
} WFSDEPENVELOPE, *LPWFSDEPENVELOPE;

typedef struct _wfs_dep_set_guidlight
{
    WORD           wGuidLight;
    DWORD         dwCommand;
} WFSDEPSETGUIDLIGHT, *LPWFSDEPSETGUIDLIGHT;

typedef struct _wfs_dep_supply_replen
{
    WORD           fwSupplyReplen;
} WFSDEPSUPPLYREPLEN, *LPWFSDEPSUPPLYREPLEN;

typedef struct _wfs_dep_power_save_control
{
    USHORT         usMaxPowerSaveRecoveryTime;
} WFSDEPPOWERSAVECONTROL, *LPWFSDEPPOWERSAVECONTROL;

/*=====*/
/* DEP Message Structures */
/*=====*/

typedef struct _wfs_dep_media_detected
{
    WORD           wDispenseMedia;
    WORD           wDepositMedia;
} WFSDEPMEDIADETECTED, *LPWFSDEPMEDIADETECTED;

typedef struct _wfs_dep_device_position
{
    WORD           wPosition;
} WFSDEPDEVICEPOSITION, *LPWFSDEPDEVICEPOSITION;

typedef struct _wfs_dep_power_save_change
{
    USHORT         usPowerSaveRecoveryTime;
} WFSDEPPOWERSAVECHANGE, *LPWFSDEPPOWERSAVECHANGE;

/* restore alignment */
#pragma pack(pop)

#ifdef __cplusplus
} /*extern "C"*/
#endif

#endif /* __INC_XFSDEP__H */

```